Composite Line Programming (Analog Line)

V1.6

#22 RAX = 1 and #23 LCC = AA1, the indexes for V4.1 Line Class Code

File Edit View Options Data Tools Window Help

Data ▼   CHAT ▼   [toolbar icons]

```
NEIL 5ESS        5e16(2)  02.00        ttyn-cdN TTY 13
  SYS EMER   CRITICAL    MAJOR    MINOR    BLDG/PWR  GLB FUNC  CKT LIM   SYS NORM
  OVERLOAD   SYS INH      AM    AM PERPH  OS LINKS      SM        CM       MISC
                                         5ESS SWITCH NEIL5ESS
SCREEN 1 OF 5                        RECENT CHANGE   1.6
(5109.5111.5111A)            COMPOSITE LINE (LINE ASSIGNMENT)

(*)1.  TN     2555008         18. MFRI          N          30. BRCS     Y
(*)2.  OE     _;_____      19. BTN (NOT=TN)  _____    31. BAUTO    N
(*)5.  PTY    _                   MULTIDN       N          32. SHARED   N
(*)6.  MLHG   ____                DEPENDN       N          33. SAUTO    N
(*)7.  MEMB   ____            22. RAX           1          34. FLS      N
                             23. LCC           AA1        35. SUSO     N
    9.  CHNG TN   3122555008      LATA          __          36. SUST     N
   10.  CHNG OE   E 0010000700 25. COIN          N          37. ICP      N
   13.  CHNG PTY  I            26. GST           N          38. RTI
   14.  CHNG MLHG ____         27. EL            N              HRI      ____
   15.  CHNG MEMB ____         28. SERHLN        _____   40. BCK LNK  N
   16.  NEW TN    _____     29. TTC           Y          41. NODL     N
Enter Review, Change-insert, Validate, screen#, or Print: █

     REPT CFTSHL TERMINAL IN SERVICE
<
```

Alt: | Host | Chat | LogonWiz | WinLink | | | Cmd Mod | Send Fax | Explorer | DOS Prm

VT-100 | Zmodem | direct connect-Com2 | 9600 | E-7-1 | rd ○ sd ○ cd ● cts ● | 13

Line Programming (Analog Line)

V1.6

Continued


```
TLWS ttyn tty13                                    _ □ ×
File  Edit  View  Options  Data  Tools  Window  Help

Data          ▼  CHAT            ▼  [toolbar icons]

NEIL 5ESS          5e16(2) 02.00        ttyn-cdN TTY 13
 SYS EMER  CRITICAL    MAJOR    MINOR   BLDG/PWR  GLB FUNC  CKT LIM  SYS NORM
 OVERLOAD  SYS INH      AM    AM PERPH  OS LINKS    SM       CM      MISC
                                       5ESS SWITCH NEIL5ESS
SCREEN 3 OF 5                          RECENT CHANGE  1.6
(5109.5111,5111A)                COMPOSITE LINE (LINE ASSIGNMENT)

78. RTNRNG       _____        95. TR303 NAILUP N      LASS FEATURES
79. PRITYRNG     _____                              96. AC ALW      Y
80. AUDRNG       N                                  97. AR ALW      Y
81. INSTRSIG     NONE                               98. COT ALW     Y
82. CONFBRG      N                                  99. PCP ALW     Y
87. NONHUNT      N                                 100. SCA GA ALW  Y
88. PRIVACY      _                                 101. SCF GA ALW  Y
89. OVRD DNY XFER N                                102. SCR GA ALW  Y
90. BUSY MONITOR N                                 103. SDA GA ALW  Y
91. ATT MLHG     1                                 104. ALT LANG    N
92. RBV TGN      _____
93. ANI7         N
Enter Review, Change-insert, Validate, screen#, or Print: █


     REPT CFTSHL TERMINAL IN SERVICE
<

Alt:   Host    Chat   LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm
 VT-100     Zmodem     direct connect-Com2     9600   E-7-1  rd ○ sd ○ cd ● cts ●   25
 Port opened - Com2                                          Connected    00:17:53
```

Line Programming (Analog Line)

V1.6

Continued

```
TLWS ttyn tty13                                                    _  □  ✕

File  Edit  View  Options  Data  Tools  Window  Help

⊞ Data              ▼   CHAT                ▼   [toolbar icons]


NEIL 5ESS          5e16(2)  02.00        ttyn-cdN TTY 13
 SYS EMER  CRITICAL     MAJOR     MINOR   BLDG/PWR  GLB FUNC  CKT LIM  SYS NORM
 OVERLOAD  SYS INH      AM     AM PERPH  OS LINKS     SM        CM      MISC
                                5ESS SWITCH NEIL5ESS
SCREEN 5 OF 5                           RECENT CHANGE  1.6
(5109,5111,5111A)            COMPOSITE LINE (LINE ASSIGNMENT)

        ASP                         USAGE SENSITIVE CALL FORWARDING
131. OFC OBL INH N              140. USCF ALW N
132. OFC ONA INH N              141. USCF ACT N
133. URT FCD BLK N                  FWDTODN        _____
     BLK LN CODE N


135. MONITORED TN N
136. CONTEXT ID   NATIVE
137. INHIBIT DEL  N

USAGE SENSITIVE SIX WAY CALLING
139. USSWC ALW N
Enter Review, Change-insert, Validate, screen#, or Print: ▮


    _____
      REPT CFTSHL TERMINAL IN SERVICE
<

Alt·   Host    Chat   LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm

 VT-100    Zmodem    direct connect-Com2      9600    E-7-1   rd ○ sd ○ cd● cts ●   30
```

Line Features (Analog Line)

V1.11


```
TLWS ttyn tty13                                                    _ □ ✕

File  Edit  View  Options  Data  Tools  Window  Help

🖳 Data              ▼   CHAT                ▼   [toolbar icons]

NEIL 5ESS            5e16(2)  02.00            ttyn-cdN TTY 13
SYS EMER  CRITICAL     MAJOR      MINOR      BLDG/PWR  GLB FUNC  CKT LIM    SYS NORM
OVERLOAD  SYS INH       AM      AM PERPH    OS LINKS     SM        CM        MISC
                                           5ESS SWITCH NEIL5ESS
SCREEN 1 OF 2                         RECENT CHANGE   1.11
(5112,5113)                       BRCS FEATURE ASSIGNMENT (LINE)

(*)1. TN 2555008      (*)2. OE  _,_____    (*)6. MLHG ____   8. BFGN CTX0001 0
                      (*)5. PTV _              (*)7. MEMB ____

                       11. FEATURE LIST (FEATLIST)
ROW FEATURE  A P AC R ROW FEATURE  A P AC R ROW FEATURE  A P AC R
 1  MDR      Y _ N  N   8 /CPUEOT  Y _ N  N  15  _____  _ _ _ _
 2  IDPLINE  Y _ N  N   9 /CPUVT   Y _ N  N  16  _____  _ _ _ _
 3  /MWCTIA1 Y _ N  N  10 /DRPP    Y _ N  N  17  _____  _ _ _ _
 4  /MWCH1   Y _ N  N  11 PPP      Y _ N  N  18  _____  _ _ _ _
 5  CWTP     Y _ N  N  12  _____  _ _ _ _ 19  _____  _ _ _ _
 6  /CWT     Y _ N  N  13  _____  _ _ _ _ 20  _____  _ _ _ _
 7  TG1      Y _ N  N  14  _____  _ _ _ _ 21  _____  _ _ _ _
Enter Review, Validate, screen#, or Print:


    REPT CFTSHL TERMINAL IN SERVICE
<

Alt:   Host    Chat   LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm

VT-100     Zmodem    direct connect-Com2      9600   E-7-1  rd ⦿ sd ⦿ cd🔴 cts 🔴   32

Port opened - Com2                                      Connected    00:25:18
```

TLWS ttyn tty13

File Edit View Options Data Tools Window Help

Data   CHAT

```
NEIL 5ESS           5e16(2)  02.00          ttyn-cdN TTY 13
 SYS EMER  CRITICAL     MAJOR      MINOR    BLDG/PWR  GLB FUNC            SYS NORM
 OVERLOAD  SYS INH      AM       AM PERPH  OS LINKS    SM        CM        MISC
                                      5ESS SWITCH NEIL5ESS
                                    RECENT CHANGE   12.33
(56241)                 MESSAGE DETAIL RECORDING FEATURE DEFINITION

*1. FEATURE NAME MDR              2. REMARKS MDR TO CL ALWAYS ACTIVE

=============================== FEATURE OPTIONS ===============================

 3. ACTYP        AUTO
 4. DCTYP        NONE
    AMAC         FLAT
 6. GRP CHNG ALW N

=============================== DEFAULT PARAMETERS ===============================

 7. MDR GROUP MDRNEIL
Enter Review, Change-insert, Validate, or Print:


     REPT CFTSHL TERMINAL IN SERVICE
<
```

Alt_   Host   Chat   LogonWiz   WinLink   Cmd Mod Send Fax Explorer DOS Prm

VT-100 | Zmodem | direct connect-Com2 | 9600 | E-7-1 | rd ○ sd ○ cd● cts ● | 53

Port opened - Com2   Connected   00:45:40

Terminal Group Feature Programming

V12.21

```
TLWS ttyn tty13                                                    [_][□][X]

File  Edit  View  Options  Data  Tools  Window  Help

[📺 Data          ▼] [CHAT                ▼] [🔤][📖][MODE][⬆][⬆][🔳][🖥][⬛][📁][🔳][🔳]

NEIL 5ESS          5e16(2)  02.00        ttyn-cdN TTY 13
SYS EMER   CRITICAL     MAJOR      MINOR      BLDG/PWR  GLB FUNC   CKT LIM   SYS NORM
OVERLOAD   SYS INH       AM      AM PERPH   OS LINKS      SM         CM        MISC
                                    5ESS SWITCH NEIL5ESS
SCREEN 1 OF 2                                RECENT CHANGE   12.21
(56071)                       TERMINAL GROUP ( FEATURE DEFINITION )

*1. FEATURE TG1                      2. REMARKS ALLOW ORIGINATE, ALLOW TERMINATE

============================== FEATURE OPTIONS ==============================

  3. ACTYP  AUTO
  4. DACTYP NONE

     ORIGINATING                         TERMINATING
  5. ORIG RSTR      NONE             8. TERM RSTR       NONE
  6. ORIG DFLT      NONE             9. TERM DFLT       NONE
  7. ORIG ERR TRMT  TONE            10. TERM ERR TRMT   TONE

Enter Review, Change-insert, Validate, screen#, or Print: ▮


     REPT CFTSHL TERMINAL IN SERVICE
<

Alt:   Host    Chat    LogonWiz   WinLink                 Cmd Mod  Send Fax  Explorer  DOS Prm

VT-100      Zmodem    direct connect-Com2          9600   E-7-1   rd ⦿ sd ⦿ cd 🔴 cts 🔴   54

Port opened - Com2                                              Connected    00:46:51
```

```
TLWS ttyn tty13                                          _ □ ×

File  Edit  View  Options  Data  Tools  Window  Help

Data            ▼   CHAT                ▼

NEIL 5ESS          5e16(2)  02.00        ttyn-cdN TTY 13
 SYS EMER   CRITICAL     MAJOR     MINOR     BLDG/PWR  GLB FUNC              SYS NORM
 OVERLOAD   SYS INH       AM      AM PERPH   OS LINKS     SM        CM         MISC
                              5ESS SWITCH NEIL5ESS
SCREEN 2 OF 2                         RECENT CHANGE  12.21
(56071)               TERMINAL GROUP ( FEATURE DEFINITION )

============================ DEFAULT PARAMETERS ============================

13. GROUP ID 1                              19. DISP RESTRICT ____
14. MOH ALW  N                              20. CNIGI           NULL

    FORWARD TO DN
15. ORIG FWD DN _____
16. TERM FWD DN _____

    ERROR ANNCMT INDEX
17. ORIG ERR ANN _____
18. TERM ERR ANN _____
Enter Review, Change-insert, Validate, screen#, or Print:


    REPT CFTSHL TERMINAL IN SERVICE
<

Alt:    Host     Chat    LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm

VT-100      Zmodem    direct connect-Com2         9600    E-7-1   rd ○ sd ○ cd● cts ●  55
Port opened - Com2                                           Connected    00:47:45
```

Precedence and Preemption Feature Programming

V12.31

#5 PRECNPP = R, (Routine) precedence level assigned when precedence code is not dialed

---

TLWS ttyn tty13

File   Edit   View   Options   Data   Tools   Window   Help

Data ▼   CHAT ▼

```
NEIL 5ESS        5e16(2)  02.00        ttyn-cdN TTY 13
 SYS EMER  CRITICAL    MAJOR     MINOR     BLDG/PWR  GLB FUNC  CKT LIM  SYS NORM
 OVERLOAD  SYS INH      AM      AM PERPH  OS LINKS     SM        CM      MISC
                                         5ESS SWITCH NEIL5ESS
SCREEN 1 OF 2                          RECENT CHANGE   12.31
(56181)                   PRECEDENCE AND PREEMPTION (FEATURE DEFINITION)

*1. FEATURE PPP              2. REMARKS PRIORITY

========================= FEATURE OPTIONS =================================

    ACTYP     AUTO          8. ATTDNTDI 0         11. AREA3DI 0
    DACTYP    NONE          9. AREA1DI  0         12. AREA4DI 0
#5. PRECNPP   R            10. AREA2DI  0         13. AREA5DI 0
 6. SATIMEOUT 0
 7. CROSSOVER Y



Enter Review, Change-insert, Validate, screen#, or Print:


     REPT CFTSHL TERMINAL IN SERVICE
<
```

Alt: Host   Chat   LogonWiz   WinLink   Cmd Mod   Send Fax   Explorer   DOS Prm

VT-100   Zmodem   direct connect-Com2   9600   E-7-1   rd ○ sd ○ cd ● cts ●   58

Port opened - Com2   Connected   00:51:15

Priority Precedence and Preemption Feature Programming

V12.31   Continued

#14 PRECREG = P, Authorized precedence outside of the assigned Community of Interest

#15 NETORIG = Y, Origination of network calls allowed

#16 NETTERM = Y, Termination of network calls allowed

#19 PREEMPT = Y,preempt for reuse occurs when preempted line is needed to complete call

#20 IMPREEMPT = Y, allows termination of calls with higher precedence

```
TLWS ttyn tty13                                                    _ □ ×

File  Edit  View  Options  Data  Tools  Window  Help

 Data              ▼   CHAT                ▼   [toolbar icons]

NEIL 5ESS          5e16(2)  02.00            ttyn-cdN TTY 13
 SYS EMER  CRITICAL    MAJOR      MINOR     BLDG/PWR  GLB FUNC  CKT LIM   SYS NORM
 OVERLOAD  SYS INH      AM      AM PERPH    OS LINKS    SM        CM        MISC
                                        5ESS SWITCH NEIL5ESS
SCREEN 2 OF 2                       RECENT CHANGE  12.31
(56181)                 PRECEDENCE AND PREEMPTION (FEATURE DEFINITION)

==================== LINE DEFAULT PARAMETERS ===============================

14. PRECREG  P      17. PRECCOI  __      20. IMPREEMPT  Y    23. DIRSTSEL  N
15. NETORIG  Y      18. COIGPID  0       21. PRECPU     N    24. HOTLINE   N
16. NETTERM  Y      19. PREEMPT  Y       22. FWDPREC    N

======= TRUNK DEFAULT PARAMETERS ==========================================

25. TRKTYPE _____       27. ESP     N     29. PRITYRNG _____
26. PRECTRK __            28. DSN103  Y


Enter Review, Change-insert, Validate, screen#, or Print:


      REPT CFTSHL TERMINAL IN SERVICE

<

Alt-    Host     Chat   LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm
  VT-100      Zmodem    direct connect-Com2        9600   E-7-1  rd ○ sd ○ cd● cts ●   00
Port opened - Com2                                              Connected    00:52:44
```

Precedence Call Waiting Feature Programming

V12.15

```
TLWS ttyn tty13                                                    _ □ ✕

File  Edit  View  Options  Data  Tools  Window  Help

📧 Data              ▼    CHAT              ▼   [toolbar icons]


NEIL 5ESS        5e16(2)  02.00        ttyn-cdN TTY 13
 SYS EMER   CRITICAL    MAJOR      MINOR    BLDG/PWR  GLB FUNC            SYS NORM
 OVERLOAD   SYS INH       AM     AM PERPH   OS LINKS     SM        CM      MISC
                                            5ESS SWITCH NEIL5ESS
SCREEN 1 OF 2                          RECENT CHANGE   12.15
(56031)                    CALL WAITING ( FEATURE DEFINITION )

*1. FEATURE  CWTP              2. REMARKS Precedence Call Waiting


=============================== FEATURE OPTIONS ===============================
   ACTIVATION                  INDICATORS             13. CDP TONE   N
3. ACTVP   AUTO           8. CDPIND   BEEP3           14. CW DELUXE  N
4. DACTVP  NONE          #9. CGPIND   RING
5. INVOKE  PTRM              DEPTONE  NONE                ALLOWED CALL ORIGIN
   FLASH   Y                                              ATTENDANT Y
                             BILLING                       INTRAOFC  Y
   BRIDGE TO FEATURE       CGPTYBILL  NORMAL               INTEROFC  Y
   MULTI WAY /MWCWAC       AMAC       FLAT                  INTRAGRP  Y
                                                           PFA       Y
Enter Review, Change-insert, Validate, screen#, or Print: ▮


     REPT CFTSHL TERMINAL IN SERVICE
<

Alt:   Host    Chat   LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm

 VT-100     Zmodem    direct connect-Com2      9600    E-7-1   rd ○ sd ○ cd ● cts ●   02

Port opened - Com2                                            Connected    00:54:34
```

```
TLWS ttyn tty13                                                    _ □ ✕

File  Edit  View  Options  Data  Tools  Window  Help

[▣ Data          ▼] [CHAT                ▼]  [🅰][📖][MODE][📤][📥][📇][▦][📠][🖥][📂][🖳][🗑]

NEIL 5ESS           5e16(2)  02.00          ttyn-cdN TTY 13
  SYS EMER    CRITICAL    MAJOR    MINOR    BLDG/PWR  GLB FUNC  CKT LIM   SYS NORM
  OVERLOAD    SYS INH      AM    AM PERPH   OS LINKS     SM       CM        MISC
                                      5ESS SWITCH NEIL5ESS
SCREEN 2 OF 2                              RECENT CHANGE   12.15
(56031)                        CALL WAITING ( FEATURE DEFINITION )


=============================== DEFAULT PARAMETERS  ===============================
    BILL AFT X    0                  MDR CALL WAITING
23. CDP TN INTVL 10                29. INHIBIT MDNL CW NONE
24. LONG DST DT  NORMAL

 CALL WAITING DELUXE
25. ALERT TYPE     OFCALERT
26. DFLT OPT       OFCDFLTOPT
27. USG SENS CONF  OFCCONF

TALKING CALL WAITING
28. TCW N
Enter Review, Change-insert, Validate, screen#, or Print:


      REPT CFTSHL TERMINAL IN SERVICE
<

[Alt₋][ Host ][ Chat ][LogonWiz][WinLink][      ][      ][Cmd Mod][Send Fax][Explorer][DOS Prm]
[ VT-100 ][ Zmodem ][direct connect-Com2  ][9600][E-7-1][rd ⦿ sd ⦿ cd● cts ●][03]
[Port opened - Com2                              ][Connected][00:55:33]
```

Individual Dialing Plan Feature Programming

V12.17

Individual Dialed Code Programming (Routine)

V9.13

#1 IDPNAME = IDPLINE, obtained from #1 FEATURE in V 12.17 Individual Dialing Feature Definition

#2 INC DIGS = 94, Routine precedence code

#3 STATE = PAUSE

#4 ACTION = PNTR, Routine precedence

#5 FEATUE = /PP*, Precedence and preemption pre-constructed feature

```
TLWS ttyn tty13                                                  _ □ ✕

 File  Edit  View  Options  Data  Tools  Window  Help

 📠 Data            ▼   CHAT            ▼   🅰 📖 ⬆ ⬆ 🔳 💻 🖥 📠 📠 🗑

 NEIL 5ESS          5e16(2)  02.00        ttyn-cdN TTY 13
 SYS EMER  CRITICAL     MAJOR     MINOR     BLDG/PWR  GLB FUNC  CKT LIM  SYS NORM
 OVERLOAD  SYS INH       AM     AM PERPH   OS LINKS    SM        CM       MISC
                                   5ESS SWITCH NEIL5ESS
 SCREEN 2 OF 2                          RECENT CHANGE  9.13
 (56011,56012)        IDP DIALED CODE ASSIGNMENT ( INDIVIDUAL DIALING )

                  14. CONFLICT RESOLUTION LIST (CONFRES.C)

 ENTRY  REM                      ACT  ICM  TRIG  DPAT     DPAT      DPAT      DPAT
 (ROW)  DIGS ACTION    FEATURE   SET RANGE NBR  1 TO 8  9 TO 16  17 TO 24 25 TO 32
   1     0  _____  _____    0    0   ____  _____ _____  _____ _____
   2     0  _____  _____    0    0   ____  _____ _____  _____ _____
   3     0  _____  _____    0    0   ____  _____ _____  _____ _____
   4     0  _____  _____    0    0   ____  _____ _____  _____ _____
   5     0  _____  _____    0    0   ____  _____ _____  _____ _____
   6     0  _____  _____    0    0   ____  _____ _____  _____ _____
   7     0  _____  _____    0    0   ____  _____ _____  _____ _____
   8     0  _____  _____    0    0   ____  _____ _____  _____ _____
 Enter Review, Change-insert, Validate, screen#, or Print:


      REPT CFTSHL TERMINAL IN SERVICE
 <

 Alt:   Host    Chat   LogonWiz  WinLink                Cmd Mod Send Fax Explorer DOS Prm
  VT-100    Zmodem    direct connect-Com2         9600   E-7-1  rd ◯ sd ◯ cd ● cts ●  06
  Port opened - Com2                                              Connected    00:58:59
```

Individual Dialed Code Programming (Routine)

V9.13

#1 IDPNAME = IDPLINE, obtained from #1 FEATURE in V 12.17 Individual Dialing Feature Definition

#2 INC DIGS = 93, Routine precedence code

#3 STATE = PAUSE

#4 ACTION = PNTP, Priority precedence

#5 FEATUE = /PP*, Precedence and preemption pre-constructed feature

```
TLWS ttyn tty13                                              _ □ ×

File  Edit  View  Options  Data  Tools  Window  Help

 Data            ▼   CHAT                    ▼

NEIL 5ESS          5e16(2)  02.00          ttyn-cdN TTY 13
 SYS EMER  CRITICAL    MAJOR     MINOR    BLDG/PWR  GLB FUNC  CKT LIM  SYS NORM
 OVERLOAD  SYS INH      AM     AM PERPH   OS LINKS    SM        CM      MISC
                                      5ESS SWITCH NEIL5ESS
SCREEN 2 OF 2                             RECENT CHANGE   9.13
(56011,56012)             IDP DIALED CODE ASSIGNMENT ( INDIVIDUAL DIALING )

             14. CONFLICT RESOLUTION LIST (CONFRES.C)

ENTRY   REM                      ACT  ICM  TRIG  DPAT    DPAT     DPAT      DPAT
(ROW)  DIGS ACTION    FEATURE    SET RANGE NBR  1 TO 8  9 TO 16  17 TO 24 25 TO 32
  1     0                         0    0
  2     0    _____   _____   0    0    ____  _____  _____  _____  _____
  3     0    _____   _____   0    0    ____  _____  _____  _____  _____
  4     0    _____   _____   0    0    ____  _____  _____  _____  _____
  5     0    _____   _____   0    0    ____  _____  _____  _____  _____
  6     0    _____   _____   0    0    ____  _____  _____  _____  _____
  7     0    _____   _____   0    0    ____  _____  _____  _____  _____
  8     0    _____   _____   0    0    ____  _____  _____  _____  _____
Enter Review, Change-insert, Validate, screen#, or Print: █

       REPT CFTSHL TERMINAL IN SERVICE
<
```

```
Alt:   Host    Chat   LogonWiz  WinLink            Cmd Mod  Send Fax  Explorer  DOS Prm
  VT-100    Zmodem    direct connect-Com2       9600  E-7-1  rd ◯ sd ◯ cd ● cts ●  09
Port opened - Com2                                            Connected   01:01:34
```

Individual Dialed Code Programming (Routine)

V9.13

#1 IDPNAME = IDPLINE, obtained from #1 FEATURE in V 12.17 Individual Dialing Feature Definition

#2 INC DIGS = 92, Routine precedence code

#3 STATE = PAUSE

#4 ACTION = PNTI, Immediate precedence

#5 FEATUE = /PP*, Precedence and preemption pre-constructed feature

```
TLWS ttyn tty13                                              _ □ ✕

File  Edit  View  Options  Data  Tools  Window  Help

 🖿 Data            ▼    CHAT              ▼   🅰 📖 ⬍ ⬆ ⬆ ⬆ ▦ ⬈ 🖳 ⬈ 🖬 ⬆

NEIL 5ESS        5e16(2)  02.00        ttyn-cdN TTY 13
 SYS EMER   CRITICAL    MAJOR    MINOR    BLDG/PWR  GLB FUNC  CKT LIM   SYS NORM
 OVERLOAD   SYS INH       AM    AM PERPH  OS LINKS     SM        CM      MISC
                                        5ESS SWITCH NEIL5ESS
SCREEN 2 OF 2                          RECENT CHANGE  9.13
(56011.56012)          IDP DIALED CODE ASSIGNMENT ( INDIVIDUAL DIALING )

                  14. CONFLICT RESOLUTION LIST (CONFRES.C)

ENTRY  REM                   ACT  ICM  TRIG  DPAT     DPAT      DPAT      DPAT
(ROW)  DIGS ACTION   FEATURE SET RANGE NBR  1 TO 8  9 TO 16  17 TO 24  25 TO 32
  1     0                     0    0
  2     0                     0    0
  3     0                     0    0
  4     0                     0    0
  5     0                     0    0
  6     0                     0    0
  7     0                     0    0
  8     0                     0    0
Enter Review, Change-insert, Validate, screen#, or Print: ▮


     REPT CFTSHL TERMINAL IN SERVICE
<

 Alt-    Host     Chat   LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm
  VT-100      Zmodem    direct connect-Com2      9600    E-7-1   rd ⬤ sd ⬤ cd🔴 cts 🔴  10
 Port opened - Com2                                          Connected    01:03:04
```

Individual Dialed Code Programming (Routine)

V9.13

#1 IDPNAME = IDPLINE, obtained from #1 FEATURE in V 12.17 Individual Dialing Feature Definition

#2 INC DIGS = 91, Routine precedence code

#3 STATE = PAUSE

#4 ACTION = PNTF, Flash precedence

#5 FEATUE = /PP*, Precedence and preemption pre-constructed feature

Individual Dialed Code Programming (Flash)

V9.13

Continued

```
TLWS ttyn tty13                                              _ □ ✕
File  Edit  View  Options  Data  Tools  Window  Help

  Data          ▼  CHAT           ▼  🅰 📖 ⇅ ⬆ ⬆ ⬛ 🔲 🖥 ✎ 🗑

NEIL 5ESS        5e16(2)  02.00        ttyn-cdN TTY 13
  SYS EMER  CRITICAL   MAJOR     MINOR    BLDG/PWR  GLB FUNC  CKT LIM  SYS NORM
  OVERLOAD  SYS INH    AM      AM PERPH   OS LINKS    SM       CM       MISC
                                    5ESS SWITCH NEIL5ESS
SCREEN 2 OF 2                         RECENT CHANGE  9.13
(56011,56012)        IDP DIALED CODE ASSIGNMENT ( INDIVIDUAL DIALING )

              14. CONFLICT RESOLUTION LIST (CONFRES.C)

ENTRY  REM                    ACT  ICM  TRIG  DPAT     DPAT      DPAT      DPAT
(ROW)  DIGS ACTION   FEATURE  SET RANGE NBR  1 TO 8  9 TO 16  17 TO 24  25 TO 32
  1     0                      0    0    _____  _____  _____  _____
  2     0                      0    0    _____  _____  _____  _____
  3     0                      0    0    _____  _____  _____  _____
  4     0                      0    0    _____  _____  _____  _____
  5     0                      0    0    _____  _____  _____  _____
  6     0                      0    0    _____  _____  _____  _____
  7     0                      0    0    _____  _____  _____  _____
  8     0                      0    0    _____  _____  _____  _____
Enter Review, Change-insert, Validate, screen#, or Print: ▮


     REPT CFTSHL TERMINAL IN SERVICE

<

Alt:   Host    Chat   LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm
  VT-100      Zmodem   direct connect-Com2       9600   E-7-1   rd ◯ sd ◯ cd 🔴 cts 🔴  14
  Port opened - Com2                                         Connected   01:06:37
```

Individual Dialed Code Programming (Routine)

V9.13

#1 IDPNAME = IDPLINE, obtained from #1 FEATURE in V 12.17 Individual Dialing Feature Definition

#2 INC DIGS = 90, Routine precedence code

#3 STATE = PAUSE

#4 ACTION = PNTFO, Flash Override precedence

#5 FEATUE = /PP*, Precedence and preemption pre-constructed feature

```
TLWS ttyn tty13                                              _ □ ✕

File  Edit  View  Options  Data  Tools  Window  Help

📧 Data              ▼   CHAT                ▼   🅰 📖 MODE 📤 📥 🖥 📊 📡 🖳 ⚜ 🗑 ☝

NEIL 5ESS          5e16(2)  02.00        ttyn-cdN TTY 13
SYS EMER  CRITICAL     MAJOR     MINOR     BLDG/PWR  GLB FUNC           SYS NORM
OVERLOAD  SYS INH      AM     AM PERPH    OS LINKS      SM        CM      MISC
                               5ESS SWITCH NEIL5ESS
SCREEN 2 OF 2                          RECENT CHANGE  9.13
(56011,56012)        IDP DIALED CODE ASSIGNMENT ( INDIVIDUAL DIALING )

            14. CONFLICT RESOLUTION LIST (CONFRES.C)

ENTRY  REM                 ACT  ICM  TRIG  DPAT     DPAT      DPAT     DPAT
(ROW)  DIGS ACTION  FEATURE  SET RANGE NBR  1 TO 8  9 TO 16  17 TO 24 25 TO 32
  1     0    _____  _____  0    0   ____  _____  _____  _____ _____
  2     0    _____  _____  0    0   ____  _____  _____  _____ _____
  3     0    _____  _____  0    0   ____  _____  _____  _____ _____
  4     0    _____  _____  0    0   ____  _____  _____  _____ _____
  5     0    _____  _____  0    0   ____  _____  _____  _____ _____
  6     0    _____  _____  0    0   ____  _____  _____  _____ _____
  7     0    _____  _____  0    0   ____  _____  _____  _____ _____
  8     0    _____  _____  0    0   ____  _____  _____  _____ _____
Enter Review, Change-insert, Validate, screen#, or Print: ▮


      REPT CFTSHL TERMINAL IN SERVICE
 <

Alt:   Host    Chat   LogonWiz  WinLink            Cmd Mod  Send Fax  Explorer  DOS Prm
 VT-100    Zmodem    direct connect-Com2       9600   E-7-1  rd ⚪ sd ⚪ cd 🔴 cts 🔴  15
 Port opened - Com2                                          Connected    01:08:14
```

Line Class Code Programming

V4.1

#1 LCC = AA1, obtained from #23 LCC V 1.6 Composite Line

#2 RAX = 1, obtained from #22 RAX V 1.6 Composite Line

#5 SCR = 1, part of the index for V 10.31 Precedence and Preemption Screening

#7 DAS = 1, the index for V 9.1 Digit Analysis Selector

Digit Analysis Selector Programming

V 9.1

#1 DAS = 1, obtained from #7 DAS V 4.1 Line Class Code

#2 PDIT = 2, the index for V 9.2 Prefix/Feature Digit

#4 LDIT = 1, the index for V 9.3 Local Digit

Prefix/Feature Digit Programming

V 9.2

#1 PDIT = 2, obtained from #2 PDIT V 9.1 Digit Analysis Selector

2 Digits to interpret = 6, the leading dialed digit (after the precedence code)

#3 Call type = LDIT, means proceed to local digit screening (V 9.3)

```
TLWS ttyn tty13                                                    _ □ ×
File  Edit  View  Options  Data  Tools  Window  Help

 Data                    ▼  CHAT                    ▼  [toolbar icons]

NEIL 5ESS         5e16(2)  02.00          ttyn-cdN TTY 13
 SYS EMER   CRITICAL    MAJOR      MINOR    BLDG/PWR  GLB FUNC              SYS NORM
 OVERLOAD   SYS INH     AM       AM PERPH   OS LINKS     SM        CM        MISC
                                          5ESS SWITCH NEIL5ESS
                                          RECENT CHANGE  9.2
 (53002)                     PREFIX / FEATURE DIGIT (OFFICE DIALING)

 *1. PDIT               2          15. NATURE OF NBR  ____
 *2. DIGITS TO INTERPRET 6         16. TRIG NBR       ____
 #3. CALL TYPE          LDIT       17. PREF TRIG NBR  ____
  5. TYP CI CALL        ____       18. ESC CODE       N
  7. FEATURE            ____       19. DFLT RT        NONE
  8. ACTION             ____       20. INH OBL        N
  9. RTI                ____       21. INH ONA        N
 10. POLYGRD            N          22. ANI BYPASS     N
 11. CODE INDEX         0          23. DENY XFER      N
 12. DESEP              0          24. RMK            USE LDIT
 13. PREFIX             NONE
 14. DIGITS TO BE DELETED 0
 Enter Review, Change-insert, Validate, or Print:


     REPT CFTSHL TERMINAL IN SERVICE
 <

Alt-    Host      Chat    LogonWiz  WinLink                    Cmd Mod  Send Fax  Explorer  DOS Prm
   VT-100      Zmodem    direct connect-Com2           9600   E-7-1   rd ○ sd ○ cd ● cts ●   7F
 Port opened - Com2                                                 Connected     00:16:28
```

Local Digit Programming

V 9.3

#1 LDIT = 1, obtained from #4 LDIT V 9.1 Digit Analysis Selector

#2 Digits to interpret = 632, the first 3 digits dialed (after precedence code)

#12 Number of Digits = 7, expected total digits in dialed number (minus precedence code)

#14 Code Index = 30, part of index for V 10.31 precedence and preemption screening

```
TLWS ttyn tty13                                                    _ □ ×
File  Edit  View  Options  Data  Tools  Window  Help

Data          ▼   CHAT                ▼  [toolbar icons]

NEIL 5ESS          5e16(2)  02.00        ttyn-cdN TTY 13
 SYS EMER   CRITICAL    MAJOR     MINOR    BLDG/PWR  GLB FUNC              SYS NORM
 OVERLOAD   SYS INH      AM      AM PERPH  OS LINKS     SM        CM        MISC
                                          5ESS SWITCH NEIL5ESS
SCREEN 1 OF 5                             RECENT CHANGE  9.3
(53003,53005)                        LOCAL DIGIT (OFFICE DIALING)

*1. LDIT            1                 15. DESEP        0
*2. INCOMING DIGITS 632               16. PREFIX       ____
 3. CALL TYPE       NORMAL            17. WZ1 REGION   _
 5. TYP CI CALL     NONCI             18. SAC OWNER    ____
 7. RTI             632               19. NATURE OF NBR ____
 8. POLYGRD         N                 20. TRIG NBR
 9. NPA             ___               21. ESC CODE     N
10. OFFCOD          ___               22. DFLT RT      NONE
11. TERM LATA       0                 23. INH OBL      N
12. NBR OF DIGITS   7                 24. INH ONA      N
13. RDIT            ___               25. ANI BYPASS   N
14. CODE INDEX      30                26. RMK          666routing test
Enter Review, Change-insert, Validate, screen#, or Print:


     REPT CFTSHL TERMINAL IN SERVICE
<

Alt-    Host    Chat   LogonWiz  WinLink                  Cmd Mod  Send Fax  Explorer  DOS Prm
   VT-100      Zmodem    direct connect-Com2         9600   E-7-1  rd ○ sd ○ cd ● cts ●   8F
Port opened - Com2                                              Connected      00:17:50
```

```
TLWS ttyn tty13                                          _ □ ×

File  Edit  View  Options  Data  Tools  Window  Help

 Data                   ▼   CHAT                   ▼

 NEIL 5ESS        5e16(2)  02.00        ttyn-cdN TTY 13
  SYS EMER   CRITICAL    MAJOR     MINOR     BLDG/PWR   GLB FUNC   CKT LIM   SYS NORM
  OVERLOAD   SYS INH      AM      AM PERPH   OS LINKS     SM         CM       MISC
                                         5ESS SWITCH NEIL5ESS
 SCREEN 2 OF 5                          RECENT CHANGE   9.3
 (53003,53005)                        LOCAL DIGIT (OFFICE DIALING)

 27. NPA SPLIT ANNC  N            LOCAL NUMBER PORTABILITY    37. NODAL IDX  _
                                  31. LNP TRIG NBR  ____      38. DN PREFD   N
 28. IMPLIED NPAS (IMPLDNPAS.I)   32. GEO PORT      N         39. GETS HPC   N
 ROW PREFIX NPA                   33. PORTED IN     N         40. DENY XFER  N
  1   ____   ___                  34. HOME LRN      N         41. REL LINK   N
  2   ____   ___                  35. LRN SCREENING N
  3   ____   ___                  36. INH DNT       N




 Enter Review, Change-insert, Validate, screen#, or Print:


 _____
     REPT CFTSHL TERMINAL IN SERVICE
 <

Alt:    Host     Chat    LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm
  VT-100      Zmodem     direct connect-Com2       9600    E-7-1   rd ○ sd ○ cd ● cts ●   9F
 Port opened - Com2                                              Connected    00:18:32
```

```
TLWS ttyn tty13                                                    _ □ ✕

File  Edit  View  Options  Data  Tools  Window  Help

📧 Data            ▼   CHAT                ▼   🅰 📖 ᴹᴼᴰᴱ ↔ ⬆ ⬆ ▣ 🖳 ᐃ 🖵 ᐃ 🖵 ⬆

NEIL 5ESS          5e16(2)  02.00          ttyn-cdN TTY 13
 SYS EMER  CRITICAL     MAJOR      MINOR     BLDG/PWR  GLB FUNC  CKT LIM   SYS NORM
 OVERLOAD  SYS INH       AM       AM PERPH   OS LINKS    SM         CM      MISC
                                    5ESS SWITCH NEIL5ESS
SCREEN 3 OF 5                              RECENT CHANGE   9.3
(53003,53005)                         LOCAL DIGIT (OFFICE DIALING)

                    42. CONFLICT RESOLUTION ENTRIES (CONFRES.C)
        NBR CALL            TYP              WZ1              OFF TERM        TRIG
    ROW DIG TYPE    RDIT CI CALL  CDI  DESEP REG RTI   POLY NPA COD LATA NON  NBR
     1   0                          0       0    _       N            0
     2   0                          0       0    _       N            0
     3   0                          0       0    _       N            0
     4   0                          0       0    _       N            0
     5   0                          0       0    _       N            0
     6   0                          0       0    _       N            0
     7   0                          0       0    _       N            0
     8   0                          0       0    _       N            0
     9   0                          0       0    _       N            0
    Enter Review, Change-insert, Validate, screen#, or Print: ▮


        REPT CFTSHL TERMINAL IN SERVICE
    <

Alt:   Host    Chat   LogonWiz  WinLink                   Cmd Mod  Send Fax  Explorer  DOS Prm
   VT-100      Zmodem    direct connect-Com2          9600   E-7-1   rd ⚪ sd ⚪ cd 🔴 cts 🔴   20F
   Port opened - Com2                                              Connected    00:19:05
```

```
TLWS ttyn tty13                                                    _ □ ×

File  Edit  View  Options  Data  Tools  Window  Help

Data                    ▼    CHAT                ▼   [toolbar icons]

NEIL 5ESS        5e16(2)  02.00          ttyn-cdN TTY 13
 SYS EMER  CRITICAL      MAJOR      MINOR    BLDG/PWR  GLB FUNC              SYS NORM
 OVERLOAD  SYS INH        AM      AM PERPH   OS LINKS    SM        CM        MISC
                                           5ESS SWITCH NEIL5ESS
SCREEN 4 OF 5                     RECENT CHANGE  9.3
(53003,53005)                    LOCAL DIGIT (OFFICE DIALING)

             42. CONFLICT RESOLUTION ENTRIES (CONFRES.C)
       ESC  SAC  DFLT INH INH ANI    LNP     GEO  PORTED HOME LRN  INH NODAL
ROW  CODE  OWN   RT  OBL ONA BYPASS  TRIG NBR PORT  IN      LRN  SCRN DNT IDX
1     N          NONE  N   N   N      ___         N      N     N    N   N    _
2     N          NONE  N   N   N      ___         N      N     N    N   N    _
3     N          NONE  N   N   N      ___         N      N     N    N   N    _
4     N          NONE  N   N   N      ___         N      N     N    N   N    _
5     N          NONE  N   N   N      ___         N      N     N    N   N    _
6     N          NONE  N   N   N      ___         N      N     N    N   N    _
7     N          NONE  N   N   N      ___         N      N     N    N   N    _
8     N          NONE  N   N   N      ___         N      N     N    N   N    _
9     N          NONE  N   N   N      ___         N      N     N    N   N    _
Enter Review, Change-insert, Validate, screen#, or Print: █

     REPT CFTSHL TERMINAL IN SERVICE
<
```

Alt- | Host | Chat | LogonWiz | WinLink | | | Cmd Mod | Send Fax | Explorer | DOS Prm

VT-100 | Zmodem | direct connect-Com2 | 9600 | E-7-1 | rd ○ sd ○ cd● cts ● | 20R

Port opened - Com2   Connected   00:19:41

```
NEIL 5ESS          5e16(2)  02.00          ttyn-cdN TTY 13
 SYS EMER   CRITICAL      MAJOR      MINOR      BLDG/PWR  GLB FUNC  CKT LIM   SYS NORM
 OVERLOAD   SYS INH        AM      AM PERPH    OS LINKS     SM        CM       MISC
                                                5ESS SWITCH NEIL5ESS
SCREEN 5 OF 5                              RECENT CHANGE   9.3
(53003,53005)                         LOCAL DIGIT (OFFICE DIALING)

42. CONFLICT RESOLUTION ENTRIES (CONFRES.C)
       DN    GETS DENY REL   NPA
ROW PREFD HPC  XFER LINK SPLIT ANNC
 1    N     N    N    N     N
 2    N     N    N    N     N
 3    N     N    N    N     N
 4    N     N    N    N     N
 5    N     N    N    N     N
 6    N     N    N    N     N
 7    N     N    N    N     N
 8    N     N    N    N     N
 9    N     N    N    N     N
Enter Review, Change-insert, Validate, screen#, or Print:

      REPT CFTSHL TERMINAL IN SERVICE
<
```

Precedence and Preemption Screening Programming

V 10.31

#1 SCR = 1, obtained from #5 SCR in V4.1 Line Class Code

#2 CDI = 30, obtained from #14 Code Index in V 9.3 Local Digit

#3 RTE Code = 0, means route digit 0 (for voice call)

#4 PREC Level = R (Routine, no precedence code dialed or precedence code 94 dialed)

#7 MC RTI = 30, index for V 10.4 BRCS MC Route Index Expansion

#12 CHGIDX = 1, index for v 10.11 Charge Index Expansion

Precedence and Preemption Screening Programming

V 10.31

#1 SCR = 1, obtained from #5 SCR in V4.1 Line Class Code

#2 CDI = 30, obtained from #14 Code Index in V 9.3 Local Digit

#3 RTE Code = 0, means route digit 0 (for voice call)

#4 PREC Level = P (Priority, precedence code 93 dialed)

#7 MC RTI = 131, index for V 10.4 BRCS MC Route Index Expansion

#12 CHGIDX = 1, index for v 10.11 Charge Index Expansion

BRCS MC Route Index Expansion Programming

V 10.4   (Routine Search Route)

#1 MC RTIDX = 30 obtained from #7 MC RTI in V 10.31 Precedence and Preemption Screening

#2 RT Type = MC

#3 TRK GP NUM = 3021, Destination trunk group

#4 SFG GP NUM = 0

#5 CHARG IDX = 1, Charge index

#7 NUM DEL = 3, delete the first 3 dialed digits

#8 PREFIX = 666, Replace the deleted digits with the digit string 666

#10 SEC MC RTIDX = 0, overflow route number (0 means no overflow route)

```
TLWS ttyn tty13                                                    _□×

File  Edit  View  Options  Data  Tools  Window  Help

  Data              ▼    CHAT              ▼

 NEIL 5ESS          5e16(2)  02.00          ttyn-cdN TTY 13
  SYS EMER   CRITICAL      MAJOR      MINOR      BLDG/PWR  GLB FUNC  CKT LIM   SYS NORM
  OVERLOAD   SYS INH        AM      AM PERPH   OS LINKS     SM        CM        MISC
                                            5ESS SWITCH NEIL5ESS
 SCREEN 2 OF 2                              RECENT CHANGE   10.4
 (5304)                             BRCS MC ROUTE INDEX EXPANSION

            CRITICAL DATA INDICATOR
 27. CRIT IND  N
 28. CRIT RMK  _____



 Enter Review, Change-insert, Validate, screen#, or Print: ▮

 _____
      REPT CFTSHL TERMINAL IN SERVICE
 <

Alt-   Host      Chat    LogonWiz  WinLink                  Cmd Mod  Send Fax  Explorer  DOS Prm
  VT-100      Zmodem    direct connect-Com2        9600    E-7-1   rd ○ sd ○ cd● cts ●   27F
 Port opened - Com2                                              Connected    00:26:00
```

BRCS MC Route Index Expansion Programming

V 10.4   (Precedence Idle Search Route)

#1 MC RTIDX = 131 obtained from #7 MC RTI in V 10.31 Precedence and Preemption Screening

#2 RT Type = MC

#3 TRK GP NUM = 3021, Destination trunk group

#4 SFG GP NUM = 0

#5 CHARG IDX = 1, Charge index

#7 NUM DEL = 3, delete the first 3 dialed digits

#8 PREFIX = 666, Replace the deleted digits with the digit string 666

#10 SEC MC RTIDX = 231, overflow route number (means search route 231 if no idle trunks are found)

#18 PREEMPTIND = N, means do not allow preemptive search in this route

```
TLWS ttyn tty13                                              _□X

File  Edit  View  Options  Data  Tools  Window  Help

📧 Data              ▼   CHAT                ▼

┌─────────────────────────────────────────────────────────────┐
│NEIL 5ESS        5e16(2)  02.00         ttyn-cdN TTY 13        │
│ SYS EMER  CRITICAL   MAJOR    MINOR    BLDG/PWR  GLB FUNC  CKT LIM  SYS NORM│
│ OVERLOAD  SYS INH     AM    AM PERPH  OS LINKS     SM      CM     MISC     │
│                                    5ESS SWITCH NEIL5ESS                    │
│SCREEN 2 OF 2                        RECENT CHANGE   10.4                   │
│(5304)                          BRCS MC ROUTE INDEX EXPANSION               │
│                                                                           │
│          CRITICAL DATA INDICATOR                                          │
│27. CRIT IND N                                                             │
│28. CRIT RMK _____                          │
│                                                                           │
│                                                                           │
│                                                                           │
│                                                                           │
│                                                                           │
│                                                                           │
│  Enter Review, Change-insert, Validate, screen#, or Print: ▮             │
│                                                                           │
│ ─────────────────────────────────────────────────────────────           │
│     REPT CFTSHL TERMINAL IN SERVICE                                       │
│ <                                                                         │
└─────────────────────────────────────────────────────────────┘

Alt:   Host    Chat   LogonWiz  WinLink              Cmd Mod Send Fax Explorer DOS Prm

VT-100    Zmodem    direct connect-Com2      9600   E-7-1  rd ○ sd ○ cd● cts ●  28F

Port opened - Com2                                        Connected    00:27:23
```

BRCS MC Route Index Expansion Programming

V 10.4   (Precedence Preemptive Search Route)

#1 MC RTIDX = 231 obtained from #10 SEC MC RTIDX in V 10.4

#2 RT Type = MC

#3 TRK GP NUM = 3021, Destination trunk group

#4 SFG GP NUM = 0

#5 CHARG IDX = 1, Charge index

#7 NUM DEL = 3, delete the first 3 dialed digits

#8 PREFIX = 666, Replace the deleted digits with the digit string 666

#10 SEC MC RTIDX = 0, overflow route number (0 means no overflow route)

#18 PREEMPTIND = Y, means allow preemptive search in this route

```
TLWS ttyn tty13                                                    _ □ ×

File  Edit  View  Options  Data  Tools  Window  Help

[≣] Data              ▼  CHAT              ▼  [toolbar icons]

NEIL 5ESS          5e16(2)  02.00          ttyn-cdN TTY 13
 SYS EMER   CRITICAL    MAJOR      MINOR     BLDG/PWR  GLB FUNC  CKT LIM   SYS NORM
 OVERLOAD   SYS INH       AM     AM PERPH    OS LINKS     SM       CM        MISC
                                          5ESS SWITCH NEIL5ESS
SCREEN 2 OF 2                          RECENT CHANGE  10.4
(5304)                             BRCS MC ROUTE INDEX EXPANSION

            CRITICAL DATA INDICATOR
27. CRIT IND  N
28. CRIT RMK  _____



Enter Review, Change-insert, Validate, screen#, or Print:


      REPT CFTSHL TERMINAL IN SERVICE
<

Alt-    Host      Chat    LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm
  VT-100       Zmodem    direct connect-Com2        9600    E-7-1   rd ● sd ● cd ● cts ●    29F
 Port opened - Com2                                              Connected    00:28:56
```

Charge Index Expansion Programming

V 10.11

#1 CHGIDX = 1, obtained from #12 CHGIDX in V 10.31

```
TLWS ttyn tty13                                                    _ □ X

File   Edit   View   Options   Data   Tools   Window   Help

Data                    ▼   CHAT                    ▼

NEIL 5ESS          5e16(2)  02.00          ttyn-cdN TTY 13
SYS EMER   CRITICAL      MAJOR      MINOR      BLDG/PWR   GLB FUNC   CKT LIM   SYS NORM
OVERLOAD   SYS INH         AM      AM PERPH   OS LINKS     SM         CM        MISC
                                             5ESS SWITCH NEIL5ESS
                                             RECENT CHANGE   10.11
(53021)                       CHARGE INDEX EXPANSION (CHARGING)

 *1. CHGIDX      1
 #2. AMATYPE     SP
  3. MBI         0
  4. WATSTYPE    __
  5. DATACI      1
  6. RMK         FREE
  7. ALT SFC     ___
  8. ALT CC      ___
  9. MAX OWATS   N




Enter Review, Change-insert, Validate, or Print: ▮


     REPT CFTSHL TERMINAL IN SERVICE
 <

Alt-   Host   Chat   LogonWiz  WinLink              Cmd Mod  Send Fax  Explorer  DOS Prm
  VT-100     Zmodem    direct connect-Com2        9600   E-7-1   rd ◯ sd◯ cd● cts ●  32F
  Port opened - Com2                                            Connected   00:31:00
```